



## SCHEDA STAMPANTE A ROTOLO SP 212



### CARATTERISTICHE TECNICHE

<b>Printer Method</b>	Serial Impact dot matrix 7 pin
<b>Number of Columns</b>	42 @ 16 cpi, 35 @ 13.4 cpi
<b>Printing Speed</b>	Approx. 2.5 lines / sec.
<b>Print Direction</b>	Bi-directional
<b>Font Configuration</b>	7 x 7 or 9 x 7
<b>Dot Spacing</b>	0.316(H) x 0.423(V) mm
<b>Character Size</b>	1.28W x 2.87H mm (7 x 7, 16 cpi)
<b>Character Set</b>	1.59W x 2.87H mm (9 x 7, 13.4 cpi)
<b>Print Area</b>	ASCII, IBM Set #2 International characters (contact Star for additional character sets)
<b>Paper Feed Method</b>	66 mm
<b>Paper Feed Speed</b>	Friction
<b>Line Spacing</b>	Approx 9 lines / sec., 15 inches / sec.
<b>Roll Paper</b>	1/6 inch
<b>Width</b>	Normal or carbonless copy paper
<b>Thickness</b>	76 +/- 0.5 mm (3.0")
<b>Copies</b>	One ply: 0.07 - 0.10 mm
<b>Roll Diameter</b>	Original + 1 copy: 0.05 - 0.08 mm (1 sheet)
<b>Core Diameter</b>	Original + 2 copy: 0.05 - 0.08 mm (1 sheet)
<b>Inked Ribbon SP212/242</b>	Total should be less than 0.2 mm
<b>Inked Ribbon SP216/246</b>	85 mm (3.35")
<b>Interface</b>	12 +/- 1 mm
<b>Data Buffer</b>	Paper end should not be glued to the core
<b>Printer Reliability</b>	Ribbon cassette purple.
<b>Head Life</b>	RC200P (2.2 million chars.)
<b>Autocutter Life</b>	Ribbon cassette red/black.
<b>Power Supply</b>	RC200BR (0.3/0.6 million chars.)
<b>Power Consumption</b>	Option: black ribbon cassette
<b>Operation Conditions</b>	(1.2 million characters)
<b>Storage Conditions</b>	Serial RS232C or Parallel versions
<b>Dimensions: SP212/216</b>	Approx. 1Kb
<b>Dimensions: SP242/246</b>	9 million lines Calculated Real Time MCBF
<b>Weight: SP212/216</b>	2.5 million lines MCBF
<b>Weight: SP242/246</b>	75 million characters
<b>Special Features</b>	300,000 cuts (SP242/246)
	Full or Partial cut
	230v, 50Hz
	Max. 24W
	0°c to 50°c, 10% to 80% RH
	(w/o condensation)
	-20°c to 70°c, 5% to 95% RH
	(w/o condensation)
	158(W) x 234(D) x 193(H) mm
	158(W) x 239.7(D) x 193(H) mm
	Approx. 3 kg
	Approx. 3.4kg
	Semi-automatic paper loading
	Windows drivers available
	Peripheral driver for cash drawer